

Please go to www.guoizel.com for product cleaning tips. Go to the Care + Maintenance selection.

Tools Required: Flathead screwdriver, Phillips screwdriver, pliers, wire cutters, wire strippers, electrical tape, safety glasses.

Assembly Instruction Sheet #IS-BKR8410K For Style BKR8410K

Light Source: (1) Medium Base Decorative Filament 60W bulb (provided), Maximum 150W, Alternate bulb (1) 42W CFL Maximum. Estimated Assembly Time: 20-30 minutes Preparation: Identify and inspect all parts before beginning installation. Check package content list and diagrams below to be sure all parts are present. If any parts are missing or damaged, do not attempt to assemble, install, or operate the fixture. Contact customer service for replacement parts. Fixture can only be mounted in the direction indicated on page 2. A Warnings and Cautions Turn off electricity at circuit breaker or main fuse box before installation. Consult a licensed electrician if in doubt. These instructions are provided for your safety. It is very important you read them completely before installing the fixture. We strongly recommend that a licensed, professional electrician perform the installation. Disconnect fixture from power source before replacing bulbs. Make sure bulbs are given sufficient time to cool before removal. Do not subject glass parts to any shock while in operation or shattering may result. Package Contents D Shade (Step 2 Continued) x 1 washer and then screwing the mounting screws or alternate short Fixture mounting screws in or out of the crossbar until the correct length is С Body achieved. Once the backplate on Fixture Body (C) is secure, remove x 1 Wahser the mounting ball and Fixture Body (C) and proceed to Step 3. Е x 1 **STEP 3 - Wire Connections** Crossbar Steel Collar F Assembly x 1 A. Use standard wire connectors (not included) to make all wire Socket Collar x 1 G connections. (Connectors are not included with fixture.) Twist x 1 Alternate connectors until wires are tightly joined together. Wrap each Edison Mounting connection with approved electrical tape and carefully stuff all the В H Bulb screw connected wires into the Outlet Box. x 1 x 2 White wire White wire from supply from fixture STEP 1 - Install Crossbar Assembly Black wire Black wire from A. Pass the supply wires through the Crossbar Assembly (A). Attach from fixture supply (or Red) M the Crossbar Assembly (A) to the Outlet Box with the head of the Ground wire Ground wire Green Ground Screw facing you. Secure it with Outlet Box Screws from supply from fixture (not included). Tighten until snug. Note: Use the Alternate Shorter Mounting Screw (B) if your Figure 3 installation requires a shorter mounting screw. STEP 4 - Install Fixture Body **Outlet Box Screws** (not included) Outlet A. Carefully tuck all wires into the outlet box and position the backplate Box of fixture body (D) over the outlet box. Align the holes in the backplate with the mounting Supply Wires Backplate screws or alternate short with Ground Wire Mounting Screw Mounting Screw Mounting Ball mounting screws. Secure or Alternate Short or Alternate Short with the previously Figure 1 Mounting Screw Mounting Screw removed mounting balls and hand tighten until Backplate B STEP 2 - Fit Backplate to snua. **Crossbar Assembly** Mounting Screw Mounting Ball or Alternate Short A. Remove mounting balls from Mounting Screw the Crossbar Assembly (A). Fit the backplate on Fixture Body (C) to the Crossbar Assembly (A) and secure with Figure 4 mounting balls. Note: The backplate on Fixture Body (C) Α should be snug against the wall STEP 5 - Install Shade to Fixture Body and the mounting balls. If not, Hex Nut and adjust the length of the mounting Lock Washer A. Place Shade (D), the Washer (E) and the Steel Collar (F) over the screw or alternate short mounting Socket as shown. Secure by threading the Socket Collar (G) onto screw on the Crossbar Assembly the Socket. Hand tighten until sung. (A) by unscrewing the Figure 2 B. This fixture uses Medium Base Decorative Filament 60W bulb (H), preassembled hex nut and lock Thank you for purchasing a Quoizel product. Need assistance with parts or assembly? Call Quoizel customer service at 1-631-273-2700 or visit us on-line at www.quoizel.com November2015 © 2015 Quoizel Inc.

